

BLACK BOX VIDEO

JIM & KAREN McALISTER
 1 EDMUND COURT
 OFF NORTH DRIVE
 BEACONSFIELD
 BUCKS HP9 1YT

TEL: (01494) 676192
 FAX: (01494) 681479

www.blackboxvideo.com
 jim.blackboxvideo@virgin.net

VAT No: 578 2219 18



TIME CODE BOX

Stock Code 116

Copyright 2008 Black Box Video

This Time Code Box is designed to feed time code and programme to a Walkman via a stereo 3.5 mm minijack. Both the programme and time code inputs have isolating transformers, and a variable level adjustment from -6 dB to -12 dB is also provided for the time code input.

BNC socket and also has an isolating transformer to prevent ground loops occurring with the camera's earth.

In addition the output to Walkman track 1 is attenuated by a variable level adjustment from -6 dB to -18 dB when fed with time code from a standard TTL level source such as a Betacam.



The programme input is via the XLR3F socket and is designed for line level 600 ohm balanced in. The transformer provides isolation from earth to prevent the output of the mixer becoming unbalanced. The programme feed is applied to track 2 of the Walkman at line level.

The level of time code fed to track 1 is adjustable via the flush control on the top of the unit to cope with different input levels.



The output of the unit can be set at mic level by cutting the two wire straps inside as indicated by the arrows.

The time code input is via the isolated

SPECIFICATION

Time Code Input voltage	2 to 5 V
Time Code Attenuation	-6 dB to -12 dB
Programme Input Level	Balanced Line Level
Programme Input Impedance	600 ohms
Output Impedance	600 ohms
Dimensions and Weight	60W x 110L x 30H mm / 205 grms

Price: £149.00
Stock Code 116