

**BLACK BOX
VIDEO**



JIM & KAREN McALISTER
1 EDMUND COURT
OFF NORTH DRIVE
BEACONSFIELD
BUCKS HP9 1YT

TEL: (01494) 676192
FAX: (01494) 681479

www.blackboxvideo.com
jim.blackboxvideo@virgin.net

VAT No: 578 2219 18



PP3 BATTERY BOX

Stock Code 115

Copyright 2008 Black Box Video

The PP3 Battery Box is designed to provide a robust alternative to our PP3 Clip Adaptor.

The 9 Volt output is available on a HRS4F

socket, pins 1 & 4.

The unit is provided with a flush slide On/Off switch and battery voltage monitor LED.

INSTRUCTIONS FOR USE

Operation

Lift the battery box holder up with a wide bladed screwdriver and insert a PP3 type battery, being careful to observe correct polarity. Slide the flush ON/OFF switch to ON position, which is nearest the green circle. The red LED should light brightly showing 9 Volt is available on the Hirose connector.

Battery Volt LED

The red LED glows bright with a fresh battery and gradually dims as the voltage reduces. At 8 Volts the LED will be normal brightness and by 7 Volts it will be very dim, indicating the battery should be changed. By 6 Volts the LED will be completely out.

The power consumption of the LED is insignificant as it is a special ultra high efficiency type. It's current consumption is about 1mA so an UltraLife battery would run the LED for about 1,800 hours!

SPECIFICATIONS

Output	9 Volts on 1 x HRS4F (pins 1 + 4)
Height	30 mm
Length	50 mm
Width	65 mm
Weight (excluding batteries)	100 grms



Price:

£49.00

Stock Code 115

**Black Box Video 1 Edmund Court Off North Drive Beaconsfield Bucks HP9 1YT 01494 676192
www.blackboxvideo.com**